



Technical Information

Remote camera control

Protocol: IPv4,RS422 (Panasonic AW series protocol)

Connection: Serial : Up to 5 cameras

IP : Up to 100 cameras

Adjustment:Pan/Tilt (Joystick),Zoom (Seesaw Switch),
Focus, Iris, Gain, Pedestal, Shutter, Detail,White Balance
(Auto, Adjust R/B Gain),Black Balance(Auto,
Adjust R/B Pedestal),Switch scene files

Switcher control

Connection:IP: 1

Supported Switcher: PANASONIC AW-HS50

Linkage:Camera Send,Tally Receive,Switcher BUS
selection

Pan/Tilt (Joystick)(PinP positioning etc...)

Interface

LAN:10BASE-T/100BASE-TX (for IP control)

5*RJ45+1*RJ45

RS422 (for Serial control)

Tally / GPI

D-sub 15PIN female

TALLY INPUT x 5 channels

GPI INPUT x 4 channels

GPI OUTPUT x 4 channels

Power Supply: DC 12 V \pm 10 %

Power Consumption: Approx. 0.5 A

Dimensions (WxHxD): 210 mm x 67 mm x 177 mm

Weight: Approx. 1.1 kg

Product Information

- Can control up to 100 AW-HE120KE series cameras via IP control

- Integrated camera and pan-tilt heads via RS422 serial control.

- Up to 100 preset positions can be saved for each Panasonic Integrated PTZ camera.

- The compact, portable half-rack width design has a built-in camera control for gain, pedestal, details and more.

- The AW-RP50E is a key component in Panasonic's first complete Internet Protocol (IP) production system,

- The AW-RP50E can be IP linked to the new switcher.

- Both IP and serial control supported

- IP link to AW-HS50E for easy dual switcher/controller operation

- Measures only 210 mm W x 67 mm H x 177 mm D

- Weighs approx 1.1 kg.

Disclaimer: Changes in the data may have been made by the manufacturer without notice.

Centas Konferens-TV AB
www.centas.se
info@centas.se

Stockholm
+46 8 724 04 00
stockholm@centas.se

Malmö
+46 40 14 38 00
malmo@centas.se

Göteborg
+46 31 84 01 00
goteborg@centas.se